

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(1)	17	1/17	#2 Beam	10	Source 4 26deg 575w	Warm Front
(2)	13	1/13	#2 Beam	8	Source 4 26deg 575w	Warm Front
(3)	15	1/15	#2 Beam	6	Source 4 26deg 575w	Warm Front
(4)	11	1/11	#2 Beam	4	Source 4 26deg 575w	Warm Front
(5)	7	1/7	#2 Beam	2	Source 4 26deg 575w	Warm Front
(6)	32	1/32	#1 Beam	13	Source 4 26deg 575w	Warm Front
(7)	27	1/27	#1 Beam	10	Source 4 26deg 575w	Warm Front
(8)	29	1/29	#1 Beam	8	Source 4 26deg 575w	Warm Front
(9)	25	1/25	#1 Beam	5	Source 4 26deg 575w	Warm Front
(10)	20	1/20	#1 Beam	2	Source 4 26deg 575w	Warm Front
(11)	57	1/57	#1 ELEC	9	Source 4 PARNel 575w	Warm Front
(12)	53	1/53	#1 ELEC	6	Source 4 PARNel 575w	Warm Front
(13)	101	1/101	#1 ELEC	3	Source 4 PARNel 575w	Warm Front
(14)	75	1/75	#3 ELEC	11	Source 4 PARNel 575w	Warm Front
(15)	73	1/73	#3 ELEC	8	Source 4 PARNel 575w	Warm Front
(16)	122	1/122	#3 ELEC	3	Source 4 PARNel 575w	Warm Front
(21)	150	1/150	Deck	5	Source 4 Jr 50deg 575w	SR Shin
(22)	154	1/154	Deck	6	Source 4 Jr 50deg 575w	SR Shin
(23)	157	1/157	Deck	7	Source 4 Jr 50deg 575w	SR Shin
(24)	158	1/158	Deck	8	Source 4 50deg 575w	SR Shin
(25)	145	1/145	Deck	1	Source 4 Jr 50deg 575w	SL Shin
(26)	151	1/151	Deck	2	Source 4 Jr 50deg 575w	SL Shin
(27)	156	1/156	Deck	3	Source 4 Jr 50deg 575w	SL Shin
(28)	155	1/155	Deck	4	Source 4 50deg 575w	SL Shin

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(31)	61	1/61	SR Ladders	1	Source 4 50deg 575w	SR Low Side
	62	1/62	"	2	Source 4 36deg 575w	"
(32)	69	1/69	SR Ladders	3	Source 4 50deg 575w	SR Low Side
	70	1/70	"	4	Source 4 36deg 575w	"
(33)	85	1/85	SR Ladders	5	Source 4 50deg 575w	SR Low Side
	86	1/86	"	6	Source 4 36deg 575w	"
(34)	89	1/89	SR Ladders	7	Source 4 50deg 575w	SR Low Side
	90	1/90	"	8	Source 4 36deg 575w	"
(35)	111	1/111	SL Ladders	1	Source 4 50deg 575w	SL Low Side
	112	1/112	"	2	Source 4 36deg 575w	"
(36)	119	1/119	SL Ladders	3	Source 4 50deg 575w	SL Low Side
	120	1/120	"	4	Source 4 36deg 575w	"
(37)	135	1/135	SL Ladders	5	Source 4 50deg 575w	SL Low Side
	136	1/136	"	6	Source 4 36deg 575w	"
(38)	139	1/139	SL Ladders	7	Source 4 50deg 575w	SL Low Side
	140	1/140	"	8	Source 4 36deg 575w	"
(41)	63	1/63	SR Ladders	9	Source 4 50deg 575w	SR Mid Side
	64	1/64	"	10	Source 4 36deg 575w	"
(42)	71	1/71	SR Ladders	11	Source 4 50deg 575w	SR Mid Side
	72	1/72	"	12	Source 4 36deg 575w	"
(43)	87	1/87	SR Ladders	13	Source 4 50deg 575w	SR Mid Side
	88	1/88	"	14	Source 4 36deg 575w	"

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(44)	91	1/91	SR Ladders	15	Source 4 50deg 575w	SR Mid Side
	92	1/92	"	16	Source 4 36deg 575w	"
(45)	109	1/109	SL Ladders	9	Source 4 50deg 575w	SL Mid Side
	110	1/110	"	10	Source 4 36deg 575w	"
(46)	117	1/117	SL Ladders	11	Source 4 50deg 575w	SL Mid Side
	118	1/118	"	12	Source 4 36deg 575w	"
(47)	133	1/133	SL Ladders	13	Source 4 50deg 575w	SL Mid Side
	134	1/134	"	14	Source 4 36deg 575w	"
(48)	137	1/137	SL Ladders	15	Source 4 50deg 575w	SL Mid Side
	138	1/138	"	16	Source 4 36deg 575w	"
(51)	65	1/65	SR Ladders	17	Source 4 36deg 575w	SR High Side
	67	1/67	"	19	"	"
(52)	66	1/66	SR Ladders	18	Source 4 36deg 575w	SR High Side
	68	1/68	"	20	"	"
(53)	81	1/81	SR Ladders	21	Source 4 36deg 575w	SR High Side
	83	1/83	"	23	"	"
(54)	82	1/82	SR Ladders	22	Source 4 36deg 575w	SR High Side
	84	1/84	"	24	"	"
(55)	116	1/116	SL Ladders	17	Source 4 36deg 575w	SL High Side
	114	1/114	"	19	"	"
(56)	115	1/115	SL Ladders	18	Source 4 36deg 575w	SL High Side
	113	1/113	"	20	"	"

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(57)	132	1/132	SL Ladders	21	Source 4 36deg 575w	SL High Side
	130	1/130	"	23	"	"
(58)	131	1/131	SL Ladders	22	Source 4 36deg 575w	SL High Side
	129	1/129	"	24	"	"
(71)		1/325	#3 ELEC	12	ColorSource PAR MO 90w	LED Bax
(72)		1/319	#3 ELEC	9	ColorSource PAR MO 90w	LED Bax
(73)		1/313	#3 ELEC	7	ColorSource PAR MO 90w	LED Bax
(74)		1/307	#3 ELEC	4	ColorSource PAR MO 90w	LED Bax
(75)		1/301	#3 ELEC	1	ColorSource PAR MO 90w	LED Bax
(76)		1/355	#4 ELEC	5	ColorSource PAR MO 90w	LED Bax
(77)		1/ 349	#4 ELEC	4	ColorSource PAR MO 90w	LED Bax
(78)		1/343	#4 ELEC	3	ColorSource PAR MO 90w	LED Bax
(79)		1/337	#4 ELEC	2	ColorSource PAR MO 90w	LED Bax
(80)		1/331	#4 ELEC	1	ColorSource PAR MO 90w	LED Bax
(91)	34	1/34	#1 Beam	11	Colortran 40deg w/Iris 1kW	Special
(92)	23	1/23	#1 Beam	7	Colortran 40deg w/Iris 1kW	Special
(93)	19	1/19	#1 Beam	3	Colortran 40deg w/Iris 1kW	Special
(94)	124	1/124	#3 ELEC	6	Colortran 40deg w/Iris 1kW	CC Special
(95)	58	1/58	#1 ELEC	8	Colortran 30deg 1kW	Special
(96)	55	1/55	#1 ELEC	5	Colortran 30deg 1kW	Special
(97)	102	1/102	#1 ELEC	2	Colortran 30deg 1kW	Special
(98)	5	1/5	Booth Rail	4	Colortran 20deg 1kW	Special
(99)	2	1/2	Booth Rail	3	Colortran 20deg 1kW	Special

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(101)	18	1/18	#2 Beam	9	Source 4 26deg 575w	Cool Front
(102)	14	1/14	#2 Beam	7	Source 4 26deg 575w	Cool Front
(103)	10	1/10	#2 Beam	5	Source 4 26deg 575w	Cool Front
(104)	12	1/12	#2 Beam	3	Source 4 26deg 575w	Cool Front
(105)	8	1/8	#2 Beam	1	Source 4 26deg 575w	Cool Front
(106)	33	1/33	#1 Beam	12	Source 4 26deg 575w	Cool Front
(107)	28	1/28	#1 Beam	9	Source 4 26deg 575w	Cool Front
(108)	24	1/24	#1 Beam	6	Source 4 26deg 575w	Cool Front
(109)	26	1/26	#1 Beam	4	Source 4 26deg 575w	Cool Front
(110)	21	1/21	#1 Beam	1	Source 4 26deg 575w	Cool Front
(111)	59	1/59	#1 ELEC	7	Source 4 PARNel 575w	Cool Front
(112)	54	1/54	#1 ELEC	4	Source 4 PARNel 575w	Cool Front
(113)	103	1/103	#1 ELEC	1	Source 4 PARNel 575w	Cool Front
(114)	74	1/74	#3 ELEC	10	Source 4 PARNel 575w	Cool Front
(115)	123	1/123	#3 ELEC	5	Source 4 PARNel 575w	Cool Front
(116)	121	1/121	#3 ELEC	2	Source 4 PARNel 575w	Cool Front
(121)	47	1/47	HL Box Booms	1	Source 4 36deg 575w	HL Box Boom 1
(122)	45	1/45	HR Box Booms	1	Source 4 36deg 575w	HR Box Boom 1
(131)	50	1/50	HL Box Booms	2	Source 4 36deg 1kW	HL Box Boom 2
(132)	49	1/49	HL Box Booms	3	Source 4 36deg 1kW	HL Box Boom 2
(133)	43	1/43	HR Box Booms	2	Source 4 36deg 1kW	HR Box Boom 2
(134)	44	1/44	HR Box Booms	3	Source 4 36deg 1kW	HR Box Boom 2

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(141)	42	1/42	HL Box Booms	4	Source 4 26deg 575w	HL Box Boom 3
(142)	40	1/40	HL Box Booms	5	Source 4 26deg 575w	HL Box Boom 3
(143)	36	1/36	HR Box Booms	4	Source 4 26deg 575w	HR Box Boom 3
(144)	35	1/35	HR Box Booms	5	Source 4 26deg 575w	HR Box Boom 3
(151)	39	1/39	HL Box Booms	6	Source 4 19deg 575w	HL Box Boom 4
(152)	41	1/41	HL Box Booms	7	Source 4 19deg 575w	HL Box Boom 4
(153)	37	1/37	HR Box Booms	6	Source 4 19deg 575w	HR Box Boom 4
(154)	38	1/38	HR Box Booms	7	Source 4 19deg 575w	HR Box Boom 4
(171)	107	1/107	#2 ELEC	3	Source 4 PARNel 575w	Apron Bax
(172)	106	1/106	#2 ELEC	2	Source 4 PARNel 575w	Apron Bax
(173)	105	1/105	#2 ELEC	1	Source 4 PARNel 575w	Apron Bax
(401)		1/429	CYC ELEC	5	ColorSource CYC 133w	Cyc
(402)		1/422	CYC ELEC	4	ColorSource CYC 133w	Cyc
(403)		1/415	CYC ELEC	3	ColorSource CYC 133w	Cyc
(404)		1/408	CYC ELEC	2	ColorSource CYC 133w	Cyc
(405)		1/401	CYC ELEC	1	ColorSource CYC 133w	Cyc
(499)	56	1/56	#1 ELEC		LED Worklights	WORKS
(500)					HOUSELIGHTS	HOUSE

Channel Hookup

Channel	Dim	Addr	Position	U#	Instrument Type & Load	Purpose
(600)	1	1/1	Booth Rail	1	Colortran 30deg 1kW	Curt Warm
	"	"	"	2	"	"
	6	1/6	"	5	"	"
	"	"	"	6	"	"